## **Phase Rotation Meter**



## **Technical Datasheet**



The K8031F has a rotary disc indication and is designed to check phase sequence on 3-phase systems, with a wide range from 110V to 600V AC. Neon lamps provided on the unit confirms whether a phase is open or to ensure the correct connection. The K8031F is small, lightweight and portable, designed for maximum ease of operation and ruggedness throughout. The large alligator clips are ideal for holding onto terminals

- IEC 61010-1 61010-1 CAT I 600V
- **Fused test leads included**
- **3-Phase neon indication**
- Checks phase sequence and open phase simultaneously
- Sealed against dust, the unit ensures reliable performance
- Small lightweight and portable
- Can check a wide range of 3-phase power source from
- Large size fused crocodile clips

## **General Specifications**

Functions	Range
AC Voltage	110 to 600V
Detection Method	Rotary Disc
Frequency Range	50 to 60Hz
Phase Rotation	Clockwise or Anti Clockwise
Visual Indication	Open phase neon lamps
Colours	Red, White, Blue
Casing	Moulded case
Weight	350g
Dimensions	106 x 75 x 40mm

Contact Us 
 Johannesburg
 Cape Town
 Durban
 Port Elizabeth
 Bloemfonteir

 011 872 5500
 021 556 3091
 031 569 1024
 041 452 1172
 051 430 4958
Branches: Port Elizabeth | Bloemfontein email: sales@major-tech.com www.major-tech.com

You in Tube